

# AL802-WAL NAC Power Extender (8 A)

www.boschsecurity.com



**BOSCH**

Invented for life



- ▶ Two (2) Class A or four (4) Class B outputs
- ▶ Input to Output Follower mode maintains synchronization of NAC devices
- ▶ AC Fail, Low Battery, and Battery Presence supervision
- ▶ LEDs indicate prior fault on one or more signaling circuit outputs
- ▶ One auxiliary power output (1 A supply current) with battery backup

The AL802-WAL NAC Power Extender is a cost-effective 8 A remote power supply and battery charger that can be connected to any 12 VDC or 24 VDC fire alarm control panel (FACP). Its primary application is to provide notification appliance circuit (NAC) expansion support that meets Americans with Disabilities Act (ADA) requirements. It can also be used to provide auxiliary power to support system accessories.

## Functions

### Battery Backup

There is a built-in charger for sealed lead-acid or gel-type batteries. The enclosure has room for two 12 VDC, 12 Ah batteries. If AC fails, there is automatic switchover (with zero voltage drop on switchover) to standby battery.

### Inputs

Power input is 115 VAC, 60 Hz, 1.45 A. There are two normally-closed (NC) dry contact trigger inputs. The unit is equipped for two Class A or two Class B FACP inputs.

### NAC Loop Supervision

In non-alarm conditions, independent loop supervision for Class A and/or Class B FACP NACs is provided. In the event of a loop trouble, the FACP is notified by the steered input (input 1 or input 2). In addition, there are common trouble output terminals (NC, C, NO) that are used to indicate general loop or system trouble. A common trouble input is provided for optional normally-closed (NC) devices to report trouble to the FACP. Two FACP signaling outputs can be employed and directed to control supervision and power delivery to any combination of the four outputs. The unit also has Loop Output trouble memory indication to help identify troublesome sporadic problems.

### Outputs

The AL802-WAL delivers electronically regulated and filtered 12 V or 24 V power to Class B or Class A NAC loop circuits. Additionally, a separate 1.0 A auxiliary output for four-wire smoke detectors is available. The 8 A maximum alarm current can be divided among the four outputs for powering NAC devices. Each output is rated at 2.5 A maximum. The outputs are Class 2 rated power limited outputs with auto reset thermal and short-circuit protection.

**Output Programming**

Each output can be independently programmed for Steady, Temporal Code 3, or Strobe synchronization. All outputs can be programmed for Input to Output Follower mode.

**Paralleling Outputs**

An individual output of 4 A can be obtained by paralleling two outputs.

**Horn and Strobe Synchronization**

The two-wire synchronization mode works with the Gentex Commander GOS Sync Mode 3, 4 and ST/HS series, the System Sensor SpectrAlert series of horns, strobes, and horn strobe combinations, and Cooper Wheelock horns, strobes, and horn strobe combinations to provide a means of synchronizing the temporal-coded horns, synchronizing the flash timing of the strobe, and silencing the horns of the horn strobe combination over a two-wire circuit while leaving the strobes active.

**Notice**

The AL802-WAL will synchronize only the horns, horn strobes and strobes that contain synchronization capability.

**Certifications and approvals**

Altronix Corp. holds these Listings and Approvals:

NFPA Complies with NFPA 72

Region	Certification	
USA	UL	UOXX: Control Unit Accessories, System (UL864)
	FM	AL802-WAL
	CSFM	see our website

**Parts included**

Quant.	Component
1	NAC power extender
1	AL802 logic board (AL800LGK9E)
1	Enclosure (red)
1	Cam lock
1	Open-frame transformer
1	Set of battery leads
1	Hardware pack
1	Literature – Installation Guide

**Technical specifications****Mechanical Properties**

Dimensions:	15.5 in. high x 12 in. wide x 4.5 in. deep (39.4 cm high x 30.5 cm wide x 11.4 cm deep)
Weight:	17 lbs (7.7 kg)

**Trademarks**

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

**Ordering information****AL802-WAL NAC Power Extender (8 A)**

8 A remote power supply/battery charger that can be connected to any 12 VDC or 24 VDC FACP  
Order number **AL802-WAL**

**Accessories****AL800LGK9E Logic Board**

Replacement board used with the AL802-WAL or AL1002WAL NAC Power Extenders; mounts in enclosure  
Order number **AL800LGK9E**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
203 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com