

# DCN-DDI Dual Delegate Interface

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Dual Delegate mode for two microphones and two voting and card panels
- ▶ Two microphone/line inputs
- ▶ Outputs to headphones or loudspeakers
- ▶ Range of mounting options
- ▶ Use for entrance/exit registration

The Dual Delegate Interface is intended for use in flush mounted custom solutions. It enables a number of functions to be added, making it suitable for chairmen and delegates. Such functions include facilities for connecting a Voting Panel, with or without a Card reader (DCN-FVCRD and DCN-FV). In addition, two separate audio inputs are provided that can also be used as line inputs. Each input can be assigned its own seat number, allowing the DCN-DDI to serve two delegate positions.

Settings are available to assign the Dual Delegate Interface for use as a delegate unit, a dual delegate, chairman unit, entrance/exit unit or ambient microphone. The ambient microphone is located in the conference venue, and automatically switched on when no other delegate unit or chairman unit microphones are active. In this way, interpreters always have audio contact with conference venue.

## Functions

- The loudspeaker output is switched off when the corresponding input is switched on
- The unit can be mounted free-standing on a tabletop, mounted on a wall, or discreetly mounted into tabletops or into the arm rests of chairs, etc.

- The unit is suitable for Hand-Held Microphones (DCN-FHH) or Pluggable Microphones (DCN-MICS, DCN-MICL) with Microphone Connection Panel (DCN-FMIC) and Microphone Control Panel (DCN-FMICB)
- The unit provides a single connection for an Intercom Handset (LBB 3555/00).

## Controls and Indicators

- Three Switches per input with the following possibilities:
  - Microphone or line selection
  - Asymmetrical microphone input, symmetrical microphone/ line input, or symmetrical microphone input with phantom power selection
  - Input attenuation selection of 0, 6, 12 or 18 dB +/- 3 dB input level fine adjustment potentiometer per input Interconnection
- Remote control inputs (switches) and outputs (LEDs) matching the DCN microphones and control panels
- Switch to select the different modes of the DCN-DDI:
  - Dual delegate
  - Chairman
  - Dual delegate, one microphone
  - Dual delegate, muted loudspeakers
  - Single delegate
  - Entrance/Exit
  - Ambient microphone

**Notice**

To use the entrance/exit mode, PC control software is also required.

**Interconnections**

- Two RJ11 connectors for Microphone Control Panel DCN-FMIC, Priority Panel DCN-FPRIOB, Voting Panel DCN-FV, Voting and Card Panel DCN-FVCRD
- RJ11 connector for Intercom Handset LBB 3555/00
- Two balanced audio inputs for line (0 dB), or microphone (-60 dB) sources, with or without a phantom power supply (2 x eight-pole 262° DIN-type socket)
- Six-pole circular connector for loop-through system cabling
- 2 m (78.7 in) cable terminated with a molded six-pole circular connector
- Two 3.5 mm (0.14 in) stereo jack sockets for connection to headphones or to loudspeaker panel (DCN-FLSP).

**Certifications and approvals**

Region	Certification
Europe	CE

**Technical specifications****Mechanical**

Mounting	On wall, under tabletop or seat, in arm rest or in cable duct
Dimensions (H x W x D) (excl. cables)	35 x 100 x 200 mm (1.4 x 3.9 x 7.9 in)
Weight	500 g (1.10 lb)
Color	Charcoal (PH 10736)

**Ordering information****DCN-DDI Dual Delegate Interface**

for flush mounted custom solutions

Order number **DCN-DDI**

**Represented by:****Americas:**

Bosch Security Systems, Inc.  
12000 Portland Avenue South  
Burnsville MN 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@us.bosch.com  
www.boschsecurity.com

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
al.securitysystems@bosch.com  
www.boschsecurity.com