

Security Escort Point Tracking Transmitters

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Supervision
- ▶ Manual duress alarm
- ▶ Low battery indication
- ▶ Flexible mounting options
- ▶ Mounting plate included

The Point Tracking Transmitter contains a unique code that is associated with the item using the transmitter. During an alarm, the transmitter sends this code to the Central Console. The Central Console software shows the item's photograph, location on a map, and any relevant information.

The transmitters are available in the following models:

Transmitter Model	Description
SEC-3402-304	Point Tracking Transmitter, 303/304MHz
SEC-3402-433	Point Tracking Transmitter, 433 MHz

System overview

During an alarm, the system sounders, strobes, or sirens generally activate within 2 seconds. The alarm signal transmits to the receivers which relay the alarm signal to the coordinator and to the Central Console. After an alarm starts, the transmitter begins supervision tracking.

Functions

Supervision

The transmitter can send a tracking signal to the Central Console every 60 minutes (user configurable), updating the transmitter's location. During periods of inactivity, the transmitter sends one status and location report to the Central Console every hour. To reset the transmitter, restore all device conditions such as tamper, loop, and magnet, to normal.

Manual Duress Alarm

During an alarm, the transmitter automatically continues to transmit every 7 seconds, providing the most current location information.

Low Battery Indication

At test mode, when the transmitter's battery needs replacement, a low battery message appears on the Central Console.

Reed Switch or External Input

The transmitter has the capacity to monitor magnetic and/or dry external contacts. External Normally Closed (NC) or external Normally Open (NO) contacts can be monitored.

Installation/configuration notes

Mounting Considerations

The Point Tracking Transmitter includes a mounting plate and end-of-line resistor. You can configure the transmitter to monitor magnetic or dry external contacts.

1. Magnetic Contacts - Mount the transmitter on the item and mount the magnet on a surface directly across from the item, such as a wall.
2. External Contacts - Mount the transmitter on the item. Use the two wires connected to the terminals inside the transmitter and an end-of-line (EOL) resistor to connect the transmitter to the contact.

Compatibility Information (SEC-3402-304)

Central Console Software	SE2000 Series
Transponder	EA500B
Receiver	EA102A-304

Compatibility Information (SEC-3402-433)

Central Console Software	SE3000 Series
Security Escort coordinator	SE-COR-433
Security Escort receiver	SE-RCV-433

Technical specifications

Transmission

Alarm Output:	Normally Closed (NC) and Closed (C)
Antenna Type:	Internal
Tamper Output:	NC
Transmission Frequency:	SEC-3402-304 - 303.825 or 304 MHz selectable by dip switch SEC-3402-433 - 433.42 MHz
Trouble Output:	Through Central Console

Electrical

Power Source:	3 VDC lithium battery or 12 VDC in
Battery Life:	Approximately 5 years battery life under normal operating conditions and with the recommended battery types. Heavy usage decreases battery life.
Battery Replacement:	Customer replaceable; Duracell® DL123A, Energizer® EL123AP, Panasonic® CR123A

Physical

Color:	Beige
Material:	Cyclocac® ABS
Properties:	Indoor only, vandal resistant
Dimensions (without Mounting Plate):	3.8 cm x 8.3 cm x 0.3 cm (1.5 in. x 3.3 in. x 0.1 in.)
Dimensions (with Mounting Plate):	3.8 cm x 8.4 cm x 2.0 cm (1.5 in. x 3.3 in. x 0.8 in.)

Environmental

Operating Temperature:	-20°C to +65°C (-4°F to +150°F)
------------------------	------------------------------------

Trademarks

Cyclocac® is a registered trademark of SABIC Innovative Plastics IP B.V.

Duracell® is a registered trademark of Duracell Inc., in the United States and/or other countries.

Energizer® is a registered trademark of Eveready Battery Company, Inc.

Panasonic® is a registered trademark of Panasonic Corporation.

Ordering information

SEC-3402-304 Point tracking transmitter, 303/304MHz

Contains a unique code that becomes associated with the item using the transmitter. Provides supervision, manual duress alarm, and low battery indication.

Order number **SEC-3402-304**

SEC-3402-433 Point tracking transmitter, 433MHz

Contains a unique code that becomes associated with the item using the transmitter. Provides supervision, manual duress alarm, and low battery indication.

Order number **SEC-3402-433**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia