

# NZ 300 LSN Hold-up and Intrusion Control Panel

[www.boschsecurity.com](http://www.boschsecurity.com)



**BOSCH**  
Invented for life

The NZ 300 LSN emergency call control panel and the BE 300 LSN keypad ensure a high level of flexibility and reliability.

This is achieved through use of the local security network LSN. A characteristic feature of the local security network LSN is that the detectors and control elements of a security system are all connected to the control panel with a single transmission unit, making efficient use of cables and ensuring compliance with regulations.

The BE 300 LSN remote keypad is deployed for operation, for signaling alarms and for displaying the status.

The NZ 300 LSN is TeleService-compliant.

## Functions

- The BE 300 LSN keypad acts as a remote display/control panel for the NZ 300 LSN. The BE 300 LSN is built into an LSN loop or LSN stub. Up to eight BE 300 LSN units can be connected.
- Assistance providers can be informed alternatively via:
  - Transmission units (ÜE)
  - Integrated dialing modems (AWUG)
  - Integrated dialers or communicators such as AT 2000 (built-in or housing-on-housing)
- 2 x acoustic and 1 x optical external warning devices (local alarm signaling).
- The following switch outputs are available:
  - Switch output for faults (1 x fault relay)
  - Switch output for alarms (1 x ÜE relay)
  - Freely programmable switch output (1 x relay)
  - Freely programmable control panel points (2 x open collector outputs)
- Up to 8 detection areas can be programmed with the NZ 300 LSN. Only detection area 1 can be the main area or control panel area. The areas are defined when programming the NZ 300 LSN.
- Four internal detection areas (4 inter-programs) can be formed by allocating detectors (freely programmable). Each area can be "internally activated" on an individual basis.
- The NZ 300 LSN is equipped with an event database for the last 1024 events. All alarms, malfunctions, deactivations and control panel resets are stored. The events, which are saved together with the date and time, can be shown on the display of the BE 300 LSN or using a PC. In addition, a print-out can be produced via a PC.

## Certifications and approvals

| Region  | Certification |                                  |
|---------|---------------|----------------------------------|
| Germany | VdS           | G 100070, C                      |
|         | VdS           | G 101806, A AWUG-NZ 300 G 101806 |
| Europe  | CE            | NZ 300 LSN                       |

## Ordering information

### NZ 300 LSN Hold-up and Intrusion Control Panel

For monitoring small objects, high security through LSN technology features, housing and connector board with integrated dialing modem (AWUG) and power supply unit

Order number **4998031142**

### Accessories

#### BE 300 LSN remote operating unit

For displaying and executing operating states and functions of the NZ 300 LSN

Order number **4998031457**

### Services

#### Equipment documentation for EMA kit execution documents in accordance with DIN VDE 0833, per hour

Order number

#### Represented by:

##### Americas:

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

##### Europe, Middle East, Africa:

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

##### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

##### China:

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

##### America Latina:

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com