

# RF920 Wireless PIR Detector

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Broad coverage area of 10 m x 12 m (35 ft x 40 ft)
- ▶ Supervisory signal is sent every 65 minutes
- ▶ Cover tamper and optional wall tamper
- ▶ Adjustable Internal coverage
- ▶ Complete status sent with every transmission

The RF920 is a high performance PIR detector that uses advanced signal processing to provide outstanding catch performance and unsurpassed false alarm immunity. It contains an RF transmitter with a maximum range of 150 m (500 ft) in open air. The RF920 is UL Listed for residential use when used with the DS7400XiV4 Control Panel, the RF3222 RF Receiver, and a wall tamper switch.

## Functions

### PIR Signal Processing

Motion Analyzer II uses multiple thresholds and timing windows to analyze timing, amplitude, duration, and polarity of signals to make an alarm decision. It tolerates extreme levels of heat and light caused by heaters and air conditioners, hot and cold drafts, sunlight, lightning, and moving headlights. There are three sensitivity settings.

## Certifications and approvals


Region	Certification	
USA	UL	ANSR: Intrusion Detection Units (UL639)
	FCC	ESV-0407-5
Canada	IC	12491021088

## Installation/configuration notes


### Battery Recommendations

The following battery types are recommended for the best operation of your detector: Duracell® DL123A, Eveready® CR123A, or Panasonic® CR123A.

**Coverage**



**Top View Broad Coverage: 10 m x 12 m (35 ft x 40 ft)**



**Side View Broad Coverage: 10 m x 12 m (35 ft x 40 ft)**

**Compatibility Information**

Receivers	Control Panels
RF3212	Solution Ultima 844, 862, and 880, CC488
RF3222	DS7400XIV4
RF3224	DS7240, DS7220, D6412, and D4412

**Mounting Considerations**

The recommended mounting height range is 2 m to 3 m (6.5 ft to 10 ft).

**Technical specifications**

**Transmission**

Frequency:	304.00 MHz
Maximum RF Power:	Less than 10 mW

**Electrical**

Battery:	3 VDC lithium battery
Battery Life:	5 or more years under normal operating conditions with recommended battery types

**Mechanical Properties**

Dimensions:	9.8 cm x 7.0 cm x 5.7 cm (3.9 in. x 2.75 in. x 2.25 in.)
-------------	---

**Environmental**

Relative Humidity:	0% to 95% (non-condensing)
Temperature (operating):	-29°C to +65°C (-20°F to +150°F) <i>For UL listed requirements, the temperature range is 0°C to +49°C (+32°F to +120°F)</i>

**Trademarks**

Duracell® is a registered trademark of the Gillette Company, USA, in the United States and/or other countries.

Eveready® is a registered trademark of Eveready Battery Company, Inc.

Panasonic® is a registered trademark of Matsushita Electric Industrial Co., Ltd.

**Ordering information**

**RF920 Wireless PIR Detector**

A high-performance PIR detector that uses advanced signal processing to provide outstanding catch performance

Order number **RF920**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com