

RF3341 Wireless Keypad

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Compatibility with the RF3224 and RF3222 Receivers
- ▶ Backlighting and key-press sounder
- ▶ Portable or mounted usability
- ▶ Panel relay or output control
- ▶ Factory programmed transmitter ID for quick and simple transmitter enrollment

The RF3341 is a one-way wireless keypad transmitter with backlighting and key-press sounder, which allows the user to arm, or disarm, and send special codes anywhere within the range of the system receivers. The RF3341 is compatible with the RF3224 Receiver and with the RF3222 Receiver. The keypad can be wall mounted or portable. Control panel programming and control panel type determine which system functions are available from the wireless keypad.

Functions

Programmable Keys

Three programmable keys are available. Summon fire, police, or emergency department personnel. A sliding cover protects the programmable keys so that you do not accidentally press them. Press the programmable keys for two seconds to transmit a message. At the end of the two seconds, the keypad beeps once to indicate that it sent a message to the alarm system.

Programmable Option Key

Program option key to control other devices such as lights.

Certifications and approvals

Region	Certification	
USA	FCC	ESV-0407-3
Canada	IC	12491021476

Installation/configuration notes

Compatibility Information

Receivers	Control Panels
RF3212	Solution Ultima 844, 862, and 880, CC488
RF3213	VR-8
RF3222	DS7400XiV4
RF3224	DS7240, DS7220, D6412, and D4412

Parts included

Quant.	Component
1	Wireless keypad
1	Wall Mounting Bracket

Technical specifications

Mechanical Properties

Dimensions

Keypad:	11.8 cm x 5.8 cm x 2.3 cm (4.65 in. x 2.3 in. x 0.9 in.)
Keypad Base:	13.0 cm x 7.2 cm x 1.5 cm (5.1 in. x 2.85 in. x 0.6 in.)

Environmental Considerations

Relative Humidity:	0% to 95% (non-condensing)
Temperature (operating):	-29°C to +65°C (-20°F to +150°F)

Power Requirements

Batteries:	3 V lithium battery
Battery Life:	Up to 3 years under normal operating conditions with recommended battery types
Recommended Battery Types:	Duracell® DL123A, Panasonic® CR123A, or SANYO® CR123A

Trademarks

Duracell® is a registered trademark of the Gillette Company, USA, in the United States and/or other countries.

Panasonic® is a registered trademark of a Matsushita Electric Industrial Co., Ltd.

SANYO® is a registered trademark of SANYO North America Corporation.

Ordering information

RF3341 Wireless Keypad

One-way wireless keypad transmitter; compatible with the RF3224 Receiver and with the RF3222 Receiver
Order number **RF3341**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com