

# RF3401 Series RF Point Transmitters

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Supervised sensor loop
- ▶ Internal reed switch
- ▶ Supervisory signal at regular intervals
- ▶ Complete status sent with every transmission
- ▶ Cover tamper

The RF3401 Series Point Transmitters includes the following models:

Model	Supervision Signal	Frequency
RF3401	65 minutes	304.00 MHz
RF3401E	15 minutes	433.42 MHz

Each transmitter model is magnetic and dry contact wireless, and appropriate for monitoring doors, windows or other dry contact devices. The models each have a cover tamper switch and RF supervision. They also have the capability to accept a supervised dry contact input from an external device. If there is no other activity, a low power level signal is transmitted to the receiver to provide supervision. Each transmission sends battery status information to the panel.

## Certifications and approvals

Region	Certification
Australia	RCM [RF3401E]
Europe	CE RF3401E: 1999/5/EC, EN60950 1992 (2nd edition) +A1 (1993) +A2 (1993) +A3 (1995) +A4 (1997), EN55022-1 Class B (1999), EN55024 (1998),

Region	Certification
	EN50130-4 (1995) +A1 (1998) +A2 (2003), EN61000-4-2 (1995), EN61000-4-3 (1997), EN61000-4-4 (1995), EN61000-4-5 (1995), EN61000-4-6 (1997), EN61000-4-8 (1994), EN61000-4-11 (1994), EN301489-3 (2000), ETS300683 (1997), EN300222-1 (1997-99), EN300220-3 (1997-99)
	CE RF3401E: 1999/5/EC, EN60950: 1993 +A1 +A2 +A3 +A4, EN300220-1: 1997, EN300683: 1997
USA	UL RF3401: AMQV: Connectors and Switches (UL634)
	FCC RF3401: ESV-0407-1
Canada	IC RF3401: 12491021017
China	CCC RF3401-CHI: 2009031901000552
Brazil	ANATEL RF3401E: 1220-05-1855

## Installation/configuration notes

For convenience, a quick install mounting base plate is included.

### Compatibility Information

The RF3401 Series RF point Transmitters are compatible with the following combinations of receivers and control panels:

Detector	Receivers	Control Panels
RF3401	RF3212	Solution Ultima 844, 862, and 880 control panels, CC488 control panels
	RF3213	VR-8 control panel
	RF3222	DS7400XiV4 control panels
	RF3224	DS7240, DS7220, D6412, D4412
RF3401E	RF3212E	Solution Ultima 844, 862, and 880 control panels, CC488 control panels
	RF3213E	VR-8 control panel
	RF3222E	DS7400XiV4 control panels
	RF3227E	DS7240, CC7240-A Solution 40 control panel
	RF3228E	Marise control panels
	RF3249E	DA (Abacus) control panels

### Technical specifications

#### Environmental Considerations

Relative Humidity:	0% to 95% (non-condensing)
Temperature (operating):	-29°C to +65°C (-20°F to +150°F) <i>For UL listed requirements, the temperature range is 0°C to +49°C (+32°F to +120°F)</i>

#### Mechanical Properties

Dimensions:	8.26 cm x 3.56 cm x 1.91 cm (3.25 in. x 1.4 in. x 0.75 in.)
-------------	--

#### Power Requirements

Batteries:	3 VDC lithium battery
Battery Life:	5+ years under normal operating conditions with recommended battery types
Recommended Battery Types:	Duracell® DS123A, Energizer® EL123AP, or Panasonic® CR123A

#### Trademarks

Duracell 0174 is a registered trademark of the Gillette Company, USA, in the United States and/or other countries.

Energizer® is a registered trademark of Eveready Battery Company, Inc.

Panasonic® is either a registered trademark of a Matsushita Electric Industrial Co., Ltd.

### Ordering information

#### RF3401 Point Transmitter (304.00 MHz)

304.00 MHz version of the RF3401 Point Transmitter.  
Order number **RF3401**

#### RF3401E Point Transmitter (433.42 MHz)

Supervised sensor loop, internal reed switch, complete status every transmission, with cover tamper. 433.42 MHz  
Order number **RF3401E**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com