

Learn Mode Water Resistant Pendant Panic Sensor

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Water and shock resistant
- ▶ Recessed panic button prevents false alarms
- ▶ Neck cord included
- ▶ Belt-clip design allows users to attach the sensor to a belt or purse
- ▶ Mounts on walls with the appropriate bracket

The Learn Mode Water Resistant Pendant Panic Sensor is activated by pressing a recessed button on the front of the sensor. The recessed button design helps to prevent false alarms. Users can wear the sensor on a belt or around the neck. Because the sensor is water resistant, users can wear the sensor while in the shower or in damp conditions.

Functions

Learn Mode Technology

Each device has a unique, programmed identity. Control panels recognize and learn the identity of each device in the system, eliminating programming errors in the field.

Installation/configuration notes

Compatibility Information

Receivers: RF3226 Quik Bridge Receiver
Quik Bridge Learn Mode Loop Receiver
(P/N: 60-660-01-95R)

Expanders: D208RF Receiver Expander
D216RF Receiver Expander

Parts included

Quantity	Component
1	Pendant panic sensor housing
1	Necklace cord
1	Literature pack

Technical specifications

Electrical

Battery:	3.6 VDC (½ AA) lithium battery (P/N: 34-026)
Battery Life:	5 years to 8 years

Mechanical

Color:	White
Dimensions:	5.7 cm x 4.4 cm x 1.9 cm (2.25 in. x 1.75 in. x 0.75 in.)
Radio Frequency:	319.5 MHz
Bandwidth:	24 kHz

Environmental

Temperature (Operating):	+4°C to +38°C (+40°F to +100°F)
--------------------------	---------------------------------

Ordering information

Learn Mode Water Resistant Pendant Panic Sensor

Includes recessed panic button to prevent false alarms
Order number **60-578-10-95**

Accessories

Wall Mount Bracket

Attaches one Learn Mode® Water Resistant Panic Pendant to a wall
Order number **80-116**

Radio Frequency Sniffer

Emits a series of beeps when RF transmission is detected
Order number **60-401**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com