

# EN1210 Series Universal Transmitters

www.boschsecurity.com



**BOSCH**

Invented for life



- ▶ Programmable as normally-open (NO) or normally-closed (NC)
- ▶ Small unobtrusive design
- ▶ Fully supervised
- ▶ Includes battery, case tamper, and mounting bracket
- ▶ Exclusive wireless protocol ensures maximum performance and reliability

The Universal Transmitters can make nearly any normally-open (NO) or normally-closed (NC) sensor a wireless device. The Universal Transmitters work with shock sensors, holdup buttons, pressure mats, temperature sensors, status relays, other devices. The line of universal transmitters contains the following products:

- EN1210 Universal Transmitter (Single-input)
- EN1210EOL Universal Transmitter with EOL Resistor
- EN1210SK Survey Transmitter
- EN1210W Door-Window Transmitter with Reed Switch
- EN1210-3600 Universal Transmitter (1 hr check-in)

The Inovonics EchoStream platform uses diversity reception and advanced signal processing to reduce dead spots in transmission areas. The transmitters have superior range and reliability, and are ideally suited for commercial or residential installations. They are fully supervised and include a battery, a case tamper, and a mounting bracket.

## System overview

### Powered by Inovonics

The Inovonics EchoStream platform, powered by Inovonics wireless mesh network technology, ensures superior range, reliability, and scalability for

commercial applications. Using a wide range of transmitters and repeaters, this proven technology provides flexibility and performance to meet the most stringent requirements.

### Wireless 900 MHz Band

The Inovonics EchoStream platform sends redundant information on several multi-frequency channels within the FCC Part 15 900 MHz band, providing superior range and reliability. In comparison, systems that use a single frequency technology can only send information on one narrow band channel. Any interference within the band can cause missed signals. With wireless registration, it is easy to add this technology to any application.

## Functions

### NO or NC Operation

The universal transmitters work with any standard NO or NC contact (15 ms duration) or sensor.

### Supervision

The cover tamper and battery activity are supervised. Monitoring helps ensure reliable operation.

**Design**

The small, unobtrusive design of the transmitters makes them suitable for multiple design needs.

**Cover Tamper**

The cover tamper switch notifies the system when an intruder attempts to remove the transmitter cover.

**Certifications and approvals**

Inovonics Wireless Corporation also holds the following approvals:

FCC Conforms to FCC Part 15 regulations

Region	Certification
Brazil	ANATEL 0881-10-5164 [EN1020EOL, EN1210W, EN1210]

**Installation/configuration notes**

The Universal Transmitters are compatible with the following products:

**Receivers**

EN4016SK	Survey Receiver
EN4200	Serial Receiver
EN4204R	LED Receiver

**Repeater**

EN5040-T	High-power Repeater
----------	---------------------

**Mounting Considerations**

The transmitters include a mounting bracket that hinges to the transmitter for easy installation. Installers simply mount the bracket and snap the transmitter into place.

**Parts included****EN1210**

Quant.	Component
1	Transmitter with cover tamper
1	3.0 V lithium battery
1	Mounting bracket
1	Hardware pack
1	Literature – Installation Instructions

**EN1210EOL**

Quant.	Component
1	Transmitter with cover tamper and EOL resistor
1	3.0 V lithium battery
1	Mounting bracket
1	Hardware pack
1	Literature – Installation Instructions

**EN1210SK**

Quant.	Component
1	Transmitter with cover tamper and clear plastic case
1	3.0 V lithium battery
1	Mounting bracket
1	Hardware pack
1	Literature – Installation Instructions

**EN1210W**

Quant.	Component
1	Transmitter with cover tamper and reed switch
1	Magnet
1	3.0 V lithium battery
1	Mounting bracket
1	Hardware pack
1	Literature – Installation Instructions

**EN1210-3600**

Quant.	Component
1	Transmitter with cover tamper
1	3.0 V lithium battery
1	Mounting bracket
1	Hardware pack
1	Literature – Installation Instructions

**Technical specifications****Electrical**

Power:	3.0 V, 1.4 Ah
Battery Replacement:	Duracell DL123A, Panasonic CR123A, or approved equivalent. Not all brands are equivalent. Use a specified brand.
Battery Life (Average):	3 to 5 years. Typical battery life shown assumes operating temperatures of +20°C to +30°C (+68°F to +86°F)

**Environmental**

Relative Humidity:	Up to 90% , non-condensing
Temperature (operating):	-20°C to +60°C (-4°F to +140°F)

**Mechanical**

Dimensions:	8.9 cm x 4.3 cm x 2.3 cm (3.5 in. x 1.7 in. x 0.9 in.)
-------------	---

**Transmission Characteristics**

Frequency:	902 MHz to 928 MHz
Check-in Time:	

EN1210-3600	1 hour
All other models:	3 min

### Trademarks

Trademark names are used throughout this document. In most cases, these designations are claimed as trademarks or registered trademarks in one or more countries by their respective owners. Rather than placing a trademark symbol in every occurrence of a trademark name, Bosch Security Systems, Inc. uses the names only in an editorial fashion and to the benefit of the trademark owner with no intention of infringing the trademark.

Duracell is a registered trademark of the Gillette Company, USA, in the United States and/or other countries.

Inovonics is a trademark of Inovonics Wireless Corporation.

Panasonic is a registered trademark of Matsushita Electric Industrial Co., Ltd.

#### Represented by:

##### Americas:

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

##### Europe, Middle East, Africa:

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

##### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

##### China:

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

##### America Latina:

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com