

# ISN-AP1, ISN-AP1-T, ISN-AP1-T-CHI Passive-infrared Detectors

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ 7.5 m x 7.5 m (25 ft x 25 ft) coverage
- ▶ Embedded microcontroller with First Step Processing (FSP)
- ▶ Draft and insect immunity
- ▶ Two-piece design
- ▶ Temperature compensation

These detectors are streamlined conventional stand-alone PIR motion detectors that economically deliver reliable performance. A Fresnel lens produces sharply-focused images throughout the field of view, providing a superior response to intruders. An embedded microcontroller performs First Step Processing (FSP), reducing false alarms and maximizing catch performance. Adjustable mounting height range, a two-piece design, and optional brackets make installation simple and flexible. Temperature compensation helps to maintain and enhance performance in variable climates.

The ISN-AP1-T model detectors offer a cover tamper switch.

## Functions

### Functions for All Models

#### Embedded Microcontroller

The microcontroller has sophisticated signal processing, including Bosch proprietary FSP and temperature compensation. The microcontroller helps the detectors work more reliably than conventional

PIR detectors that compare sequential signals with a fixed threshold level, offering superior false alarm immunity.

#### Signal Processing

First Step Processing (FSP) almost instantly responds to human targets without producing false alarms from other sources. FSP adjusts the detector's sensitivity based on signal amplitude, polarity, slope, and timing. This eliminates the need for the installer to select the sensitivity level.

#### Draft and Insect Immunity

The sealed optical chamber prevents drafts and insects from affecting the detector.

#### Two-piece Design

During installation and mounting, you only need to remove the cover. The circuit board and optics stay intact, increasing installation speed, ease, and effectiveness.

#### Temperature Compensation

The detector adjusts PIR sensitivity to identify human intruders at critical temperatures, detecting human body heat more accurately and avoiding false alarms.

**Test Features**

A red light emitting diode (LED) indicates alarms and activates during a walk test.

**Additional Functions for ISN-AP1-T and ISN-AP1-T-CHI Models**

**Cover Tamper Switch**

A normally-closed contact opens when the cover is removed, alerting the control panel.

**Enable or Disable LED**


Enable or disable the LED indicator with the LED jumper.

**Certifications and approvals**

Europe	EN	ISN-AP1-T: EN50131-2-2 Grade 2, Environmental Class II ISN-AP1: EN50131-2-2 Grade 1, Environmental Class II
--------	----	--


Region	Regulatory compliance/quality marks	
Germany	VdS	H 110009_Eng (ISN-AP1, ISN-AP1-T)
Europe	CE	[ISN-AP1, ISN-AP1-B, ISN-AP1-P, ISN-AP1-T]
	EN50131	EN 50131-2-2, Grade 1 (ISN-AP1)
USA	UL	ANSR (UL 639), ANSR7 (ULC-S306) [ISN-AP1, ISN-AP1-T]
	UL	20190115; UL639 – Standard for Intrusion-Detection Units
China	CCC	2009031901000547 [ISN-AP1-B-CHI, ISN-AP1-P-CHI, ISN-AP1-T-CHI]
the Netherlands	NCP	2011063 [ISN-AP1, ISN-AP1-T]

**Installation/configuration notes**



**Top View**


**Broad Coverage: 7.5 m x 7.5 m (25 ft x 25 ft)**



**Side View**

**Upper Mounting Height Range**

**Broad Coverage: 7.5 m x 7.5 m (25 ft x 25 ft)**



**Side View**

**Lower Mounting Height Range**

**Broad Coverage: 7.5 m x 7.5 m (25 ft x 25 ft)**

**Power Considerations**

- Use an approved limited power source. Connect all outputs to safety extra-low voltage (SELV) circuits only.
- The detectors have no internal standby battery.

**Mounting Considerations**

To adjust the mounting height, slide the detector’s printed circuit board (PCB) up or down before installation. Select one of these height ranges:

- 2.0 m to 2.4 m (6.6 ft to 7.9 ft)
- 2.4 m to 2.8 m (7.9 ft to 9.2 ft)

The default height is 2.4 m to 2.8 m (7.9 ft to 9.2 ft). Mount the detector in an indoor area where an intruder must cross the coverage pattern. You can mount the detector in a corner or on a flat wall (surface, semi-flush) using the optional B335-3 Low-profile Swivel-mount Bracket or on the ceiling using the optional B338 Ceiling-mount Bracket.



**Notice**

An optional mounting bracket can reduce the detector's range and increase the dead zone areas.

Do not mount the detector outdoors, on or near windows, directly in sunlight or air currents, near air conditioning outlets, heat sources, or animals.

**Compatibility Information**

Each detector model works with all conventional control panels.

**Technical specifications**

**Enclosure Design**

Color:	White
Dimensions:	93 mm x 52 mm x 44 mm (3.7 in. x 2.1 in. x 1.7 in.)
Material:	High-impact ABS plastic

**Environmental Considerations**

Relative Humidity:	0 to 95%, non-condensing
Temperature (Operating):	0°C to +49°C (+32°F to +120°F)
Temperature (Storage):	-29°C to +49°C (-20°F to +120°F)

**Indicators**

Alarm Indicator:	Red LED On ISN-AP1-T and ISN-AP1-T-CHI, enable or disable using the LED jumper.
------------------	--

**Outputs**

Relay:	Supervised Form A normally-closed (NC) contacts rated for 125 mA, 28 VDC, 3 W.
Tamper (ISN-AP1-T):	Normally-closed (NC) contacts (with cover on) rated at 28 VDC, 125 mA maximum. Connect tamper circuit to 24-hour protection circuit.

**Power Requirements**

Current (Alarm):	< 25 mA
Current (Standby):	< 15 mA at 12 VDC
Voltage (Operating):	9 VDC to 15 VDC

**Ordering information****ISN-AP1 Motion detector, 25ft (7.5m)**

Provides PIR, 7.5 m x 7.5 m (25 ft x 25 ft) coverage.  
Order number **ISN-AP1**

**ISN-AP1-T Motion detector with tamper 25ft (7.5m)**

Provides PIR, 7.5 m x 7.5 m (25 ft x 25 ft) coverage with tamper detection.  
Order number **ISN-AP1-T**

**Accessories****B335-3 Mounting bracket, swivel, low profile**

Swiveling, low-profile, universal bracket for wall mounting. The vertical swivel range is +10° to -20°, while the horizontal swivel range is ±25°. Order number **B335-3**

**Represented by:**

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
emea.securitysystems@bosch.com  
emea.boschsecurity.com

**Germany:**  
Bosch Sicherheitssysteme GmbH  
Robert-Bosch-Ring 5  
85630 Grasbrunn  
Germany  
www.boschsecurity.com

**North America:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
onlinehelp@us.bosch.com  
www.boschsecurity.us

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia