

Programming a D9412GV4/D7412GV4 Control Panel v2.00 and higher for SIA Compliance

Parameter name	Required settings for GV4 v2.0 control panels for SIA Compliance	Default
Phone #	(Prefix backup phone number with Call Waiting disable command)	{Blank}
Duress Type	Option 3	0 (Disabled)
Cancel Reports	Yes	Yes
Exit Delay Time	45 sec to 255 sec	60 sec
Duress Enable	Yes	No
Exit Delay Restart	Yes or No	Yes
All On - No Exit	Yes or No	Yes
Two Man Rule?	No	No
Early Ambush?	No	No
Exit Delay Warning	Yes	Yes
Burg Time ¹	6 min to 90 min	6 min
Alarm Bell	1 to 128 (64), A, B, C	A (on-board alarm output)
Verify Time	10 sec to 60 sec	60 sec
Entry Tone	Yes or No	Yes
Exit Tone	Yes or No	Yes
Abort Display	Yes or No	Yes
Cancel Display	Yes or No	Yes
Passcode Enter Function	Arm/Disarm	Arm/Disarm
Dual Authentication	No	No
All On Instant	- (Disabled)	- (Disabled)
Part On Instant	- (Disabled)	- (Disabled)
Send Duress	- (Disabled) or E (Enabled)	E (Enabled) ²
Disarm	- (Disabled) or E (Enabled)	E (Enabled) ²
Passcode Disarm	- (Disabled) or E (Enabled)	E (Enabled) ²
Entry Delay	30 sec to 240 sec	30 sec
Alarm Abort	Yes or No	Yes ³
Abort Window	15 sec to 45 sec	30 sec
Passcode Length	3 to 6 digits	Disabled
Swinger Bypass Count	1 to 2 trips	2 trips
Remote Warning	Yes	Yes
Cross Point Timer	5 to 255 sec	20 sec
Cross Point	Yes or No	No

¹The SIA allowed range is 1 min to 90 min. Must additionally comply with UL requirements.

²L14 is the default duress authority level.

³The default for Alarm Abort is No for P3, P4, P5, P6, P22, and 31.

Copyright

This document is the intellectual property of Bosch Security Systems, Inc. and is protected by copyright. All rights reserved.

Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

Bosch Security Systems, Inc. product manufacturing dates

Use the serial number located on the product label and refer to the Bosch Security Systems, Inc. website at <http://www.boschsecurity.com/datecodes/>.

