

B10R Enclosure, medium, red

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Easy to install standoff locations for mounting supporting modules
- ▶ Made with cold-rolled steel with a red matte finish for fire applications
- ▶ Easy access mounting locations for optional transformers
- ▶ Punch outs for optional B46 External Annunciator (for B465 only)

The B10R Medium Control Panel Enclosure is a red enclosure made of cold-rolled steel that is 1.0 mm (20 gauge) thick. It houses many different Bosch control panels and modules. The enclosure holds one 18Ah battery or two batteries (up to 7Ah).

It is compatible with the following accessories:

- **D101 Lock and Key Set.** Standard lock set with one key supplied. Uses the D102 (#1358) replacement key.
- **D110 Tamper Switch.** Screw-on tamper switch that fits all enclosures. Shipped in packages of two.
- **ICP-EZTS Dual Tamper Switch.** Combination tamper switch with a wire loop for additional tamper outputs.

Certifications and approvals

Region	Regulatory compliance/quality marks	
USA	UL	S1871-19850314-CertificateofCompliance
	UL	UL 985 - Household Fire Warning System Units (6th edition)
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems (10th edition)

Region	Regulatory compliance/quality marks	
	FDNY-CoA	6307 B465_NYC_CoA_6307
Canada	ULC	[D8108A, D8108AH, D8109, D8109G, D8109H, D8109L, B8103, D8103, B12, B10, B10R, B11, B11R

Installation/configuration notes

Compatibility

Devices	B465 Conettix Universal Dual Path Communicator B46 External Annunciator D101 Lock and Key Set ICP-EZTS Tamper Switch Set D110 Tamper Switch
---------	---

Parts included

Quantity	Component
1	Enclosure
1	Hardware pack
1	Installation Manual

Technical specifications

Properties

Dimensions	14 in x 12.5 in x 3 in (35.6 cm x 31.8 Cm x 7.6 cm)
Material	1.0 mm (20 gauge) cold-rolled steel
Color	Red

Environmental considerations

Mounting considerations	Mount in dry indoor locations.
-------------------------	--------------------------------

Ordering information

B10R Enclosure, medium, red

Red, steel enclosure. Accepts an optional lock and tamper switch.

Order number **B10R**

Accessories

D101 Enclosure lock and key set

Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.

Order number **D101**

ICP-EZTS Dual tamper switch

Combination tamper switch with a wire loop for additional tamper outputs.

Order number **ICP-EZTS**

D110 Tamper switch for enclosure, 2pcs

Screw-on tamper switch that fits all enclosures. Shipped in packages of two.

Order number **D110**

Represented by:

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia