# **D8125 Expansion module**

www.boschsecurity.com





The D8125 Addressable Expansion Module works with the D9127U or D9127T POPIT Modules to provide multiplex technology that combines zone or point supervision with individual device addressing on one pair of wires. Use the D8125 to provide expansion beyond the standard number of control panel zones, up to a total of 238 points. Each D8125 module can fully supervise 119 D9127U or D9127T POPIT Modules.

## System overview

Each D8125 installs in the control panel enclosure or in an adjacent approved enclosure. Future system expansion is very economical as D9127U or D9127T POPITs can be spliced in anywhere along the two-wire data expansion loop from the D8125 module. The D9127 is a compact, addressable device that is suitable for applications where specifications call for point identification from each initiating device or series of devices. The units are small, and easily installed in standard outlet boxes, above false ceilings, closets, or other accessible locations.

The D8125 includes a 33 k $\Omega$  end-of-line (EOL) resistor. Install the resistor at the farthest point on the loop for proper supervision.

Certific	cations	and ap	provals

Austra	lia		
Austra	lla		

C-Tick	
O HOR	

- Provides point identification of initiating devices
- Supervises wiring to devices for circuit integrity
- Expands the number of points in the system
- Compact size
- ▶ Terminal connections for reliability

Region	Regulato	ory compliance/quality marks
USA	UL	AMCX: Central Station Alarm Units (UL1610, UL1635), AMCX7: Central Station Alarm Units Certified for Canada (cULus), AOTX: Local Alarm Units (UL464, UL609), AOTX7: Local Alarm Units Certified for Canada (cULus), APAW: Police Station Alarm Units (UL365, UL464), APAW7: Police Sta- tion Alarm Units Certified for Canada (cULus), APOU: Proprietary Alarm Units (UL1076), APOU7: Proprietary Alarm Units Certified for Canada (cULus), NBSX: Household Burglar Alarm System Units (UL1023), NBSX7: Household Burglar Alarm System Units Certified for Canada (cULus), UOJ2: Control Units, System (UL864, 9th edition), UTOU: Control Units and Accessories - House- hold System Type (UL985), UTOU7: Control Units and Accessories - House- hold System Type Certified for Canada (cULus)
	UL	UL 985 - Household Fire Warning Sys- tem Units (6th edition)
	UL	UL 864 - Standard for Control Units and Accessories for Fire Alarm Systems (10th edition)
	FM	
	CSFM	California State Fire Marshal (see our website)

Region	Regulate	ory compliance/quality marks
	FDNY- CoA	6286 D7412GV4 D9412GV4 NYC COA 6286 2018-2021
	FDNY- CoA	6059 [D9412GV3 & D7412GV3]
	NYC- MEA	12-92-E, Vol. 12 12-92-E, Vol. 12
	NYC- MEA	12-92-E, Vol. 15 12-92-E, Vol. 15
	NYC- MEA	12-92-E, Vol. II 12-92-E, Vol. II
Canada	ULC	CAN/ULC S304 - Standard for Signal Re- ceiving Center and Premise Burglar Alarm
	ULC	S303 - Local Burglar Alarm Units and Systems
	ULC	ULC 365 - Police Station Connected Bur- glar Alarm Units
	ULC	APOU7.S1871 Proprietary Alarm Units Certified for Canada
	ULC	ULC-ORD C1023 - Household Burglar Alarm System Units

D9412/D7412/D7212 ٠ • D7212B1 • D9112/D9112B1 . D8112G1/D8112G2 . D9124 **Parts included** Quantity Component Expansion board 1 1 Hardware pack Literature pack 1 **Technical specifications Properties** Dimensions: 13 cm x 8 cm x 2 cm (5 in. x 3 in. x 0.75 in.) **Power Requirements** Current Draw: 50 mA for each D8125 module Voltage (Operating): 12 VDC **Ordering information** 

• D9412GV2/D7412GV2/D7212GV2

# Installation/configuration notes

#### **Compatible Control Panels**

- B9512G/B9512G-E
- B8512G/B8512G-E
- D9412GV4/D7412GV4/D7212GV4
- D9412GV3/D7412GV3/D7212GV3

D8125 Expansion module Provides expansion up to 238 POPIT devices. Order number D8125

#### Represented by:

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5600 JB Eindhoven, The Netherlands Phone: + 31 40 2577 284 emea.securitysystems@bosch.com emea.boschsecurity.com

Germany: Bosch Sicherheitssysteme GmbH Robert-Bosch-Ring 5 85630 Grasbrunn Germany www.boschsecurity.com

North America: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 onlinehelp@us.bosch.com www.boschsecurity.us

### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2699 apr.securitysystems@bosch.com www.boschsecurity.asia

© Bosch Security Systems 2020 | Data subject to change without notice 2537783947 | en, V16, 25. Jun 2020