



Rod antenna with 20 m cable



Rod antenna for exterior and interior incl. cable, 20 m, FME connector, female, pre-configured incl. mounting bracket

The attenuation of the entire system depends on the length of the antenna cable.

Technical Specifications

Rod antenna

Transmission frequency	900/1800 MHz
Impedance	50 Ohm
Gain (without cable)	3.5 dBi
Max. output	20 W
Radiator length	250 mm
Distance radiator-installation surface	150 mm

Ordering Information

Rod antenna with 20 m cable

4998131136

With FME connector, female, incl. mounting bracket for exterior and interior areas

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Bosch Security Systems Pte Ltd
38C Jalan Pemimpin
Singapore 577180
Phone: +65 6319 3450
Fax: +65 6319 3499
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by