# ATE X.25 (Installation Module) Alarm Receiver

www.boschsecurity.com





- Receipt via the X.25 network
- VdS 2465 transmission protocol
- Connection to receiving stations with X.25 access
- Installation module for UGM 2020-EAPS6

The ATE X.25 is installed in the UGM 2020 control panel and is responsible for transmitting and receiving the VdS 2465 protocols via the data transmission services network (X.25).

## Functions

Alarm messages (VdS 2465 protocol) are transmitted on the ISDN network (X.31) with transfer to the data transmission services network (X.25) and received by the ATE X.25 of the receiving station.

The ATE X.25 is programmed via the BasiLoad.exe programming software.

## **Certifications and approvals**

Countr y	Approval	ATE X.25
DE	BZT	D 131315 J
EU	BZT	D 131314 J

Installation/configuration notes

Max. 64 subscribers can be connected to an ATE X.25.

ACCESS ≥ 100 of Telekom must be applied for. The Telekom business connection (data transmission services) is prerequisite for the X.25 access. Telekom (Germany) provides the data network connection device DNG.

The ATE X.25 can be installed in the UGM 2020 EPC3 /  $\geq$  EAPS6.

For the installation of each installation module in a UGM, an SGK is a prerequisite.



## Notice

Not included in the scope of delivery are: Programming cable (laptop) X.25 (DNG/XTA) interface cable Telekom's DNG

# **Parts included**

Туре	Qty.	Component		
ATE X.25 installation module	1	ATE installation module on component carrier UGM 2020, incl.: - SGK-XTA interface cable - Power supply cable - Fitting panel for XTA in UGM - Split ferrite sleeve		

# **Technical specifications**

ATE X.25 installation module

Supply voltage	+5 V			
Current consumption in operation	500 mA			
Environmental conditions				
Ambient temperature	(0°C to +50°C)			
Environmental class	ll			
Protective system	IP 30			
Protection class	II			

# **Ordering information**

ATE X.25 (Installation Module) Alarm Receiver Order number 4998104221

### Represented by:

#### Americas:

Americas: Bosch Security Systems, Inc. 130 Perinton Parkway Fairport, New York, 14450, USA Phone: +1 800 289 0096 Fax: +1 585 223 9180 security.sales@us.bosch.com www.boschsecurity.us

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

Asia-Pacific: Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2699 apr.securitysystems@bosch.com www.boschsecurity.asia

#### China:

Bosch (Shanghai) Security Systems Ltd. 201 Building, No. 333 Fuquan Road North IBP Changning District, Shanghai 200335 China Phone +86 21 22181111 Fax: +86 21 22182398 www.boschsecurity.com.cn

## America Latina:

America Latina: Robert Bosch Ltda Security Systems Division Via Anhanguera, Km 98 CEP 13065-900 Campinas, Sao Paulo, Brazil Phone: +55 19 2103 2860 Fax: +55 19 2103 2862 Iatam.boschsecurity@bosch.com www.boschsecurity.com www.boschsecurity.com

@ Bosch Security Systems 2013 | Data subject to change without notice 1443061643 | en, V1, 01. Oct 2013