

# DS7446KP Series LCD Keypads

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Contemporary vertical design
- ▶ Flip door that covers or uncovers the illuminated keys
- ▶ Area indicator
- ▶ Adjustable volume
- ▶ Programmable emergency keys

The DS7446KP is a four-wire alphanumeric liquid crystal display (LCD) keypad that works with DS7200 Series Control Panels. It supports all system functions. The keypad is required for programming the control panel locally.

## Functions

### Contemporary Design

The compact vertical design uses less wall space and blends well into surroundings. Close the flip door to protect the keys from dirt and damage, and to conceal the illumination.

### Area Indicator

The keypad display can show area icons. The state of the icon (on, fast flash, slow flash, or off) indicates information about an area such as: the area is armed, the area is in alarm, the area has a zone trouble condition, or the area is disarmed. The keypad display can also show the area it is currently assigned to if the keypad is outside its home area.

### Indicators and Tones

The keypad display has four light emitting diodes (LEDs) across the faceplate to indicate the status for perimeter, power, arming, and command. The keypad can emit eight tones to indicate a situation such as an alarm, trouble, error, or entry delay.

### Programmable Keys

Each DS7446KP Keypad model has 19 illuminated keys for specific functions. Your installing company can program the [A], [B], and [C] keys with functions such as Emergency, Fire, or Panic. When pressed, each key emits a muted beep.

### Adjustable Volume

You can adjust the keypad volume. When the sounder is active, pressing any key on the keypad momentarily silences the sounder.

## Certifications and approvals

Region	Certification
Europe	CE 2004/108/EC EMC Directive (EMC), 2006/95/EC Low-Voltage Directive (LVD) [-EX, -SE, -ES, -FR, -NL]
Belgium	INCERT B-509-0004/c

## Installation/configuration notes

### Compatibility Information

The DS7446KP Keypad works with the DS7200 Series Control Panels.

### Wiring Considerations

Wire Type	Keypad Distance from Control Panel
Unshielded, 0.8 mm (#22 AWG)	Up to 305 m (1000 ft)
Unshielded, 1.2 mm (#18 AWG)	Up to 610 m (2000 ft)

## Parts included

Quantity	Component
1	Keypad
1	Wall tamper spring

## Technical specifications

### Environmental Considerations

Relative Humidity	80% at 40°C (100°F), non-condensing
Temperature (Operating):	+5°C to +40°C (40°F to 100°F)
Temperature (Storage):	-10°C to +55°C (14°F to 130°F)

### Power Requirements

Current (Standby):	35 mA
Current (Alarm):	100 mA
Voltage (Operating):	10.2 VDC

### Product Characteristics

Dimensions:	13.7 cm x 7.6 cm x 2.4 cm (5 in. x 3 in. x 1 in.)
Weight:	0.168 kg (0.37 lb)

## Ordering information

### DS7446KP-EX LCD Keypad

For export. Provides volume controls and three programmable emergency keys.

Order number **DS7446KP-EX**

### DS7446KP-SE LCD Keypad

For use in Sweden. Provides volume controls and three programmable emergency keys.

Order number **DS7446KP-SE**

### DS7446KP-FR LCD Keypad

For use in France. Provides volume controls and three programmable emergency keys.

Order number **DS7446KP-FR**

### DS7446KP-NL LCD Keypad

For use in the Netherlands. Provides volume controls and three programmable emergency keys.

Order number **DS7446KP-NL**

### DS7446KP-DE LCD Keypad

For use in Germany. Provides volume controls and three programmable emergency keys.

Order number **DS7446KP-DE**

### DS7446KP-ES LCD Keypad

For use in Spain. Provides volume controls and three programmable emergency keys.

Order number **DS7446KP-ES**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com