

# RF3502 Panic Key Fob (304 MHz)

www.boschsecurity.com



**BOSCH**  
Invented for life

- ▶ Panic Code Sending
- ▶ Water-immune housing

The RF3502 Panic Key Fob sends a panic alarm to the security system when both panic buttons are pressed for 3 seconds. It is protected by a water-immune housing. The range may be up to 150 m (500 ft) in open air.

## Functions

### Panic code sending

The RF3502 sends a panic code if both keys are pressed for 3 seconds. By pressing one key for 4 seconds, a panic code is sent, too.

## Certifications and approvals

Region	Certification	
USA	FCC	ESV-0407-2

## Installation/configuration notes

### Compatibility Information

Receivers	Control Panels
RF3212	Solution Ultima 844, 862, and 880, CC488
RF3213	VR-8
RF3222	DS7400XIV4
RF3224	DS7240, DS7220, D6412, and D4412

## Technical specifications

### Environmental Considerations

Relative Humidity:	0% to 85% (non-condensing)
Temperature (operating):	-29°C to +65°C (-20°F to +150°F)

### Mechanical Properties

Dimensions:	6.3 cm x 3.8 cm x 1.3 cm (2.5 in. x 1.5 in. x 0.5 in.)
-------------	-----------------------------------------------------------

### Power Requirements

Batteries:	Two 3 VDC lithium coin cell batteries
Battery Life:	5+ years

## Ordering information

### RF3502 Panic Key Fob (304 MHz)

Sends panic code when both keys are pressed for 3 seconds

Order number **RF3502**