

FLEXIDOME IP 4000i



The 1080p dome cameras from Bosch are professional surveillance cameras that provide high quality HD images for demanding security and surveillance network requirements. These domes are true day/night cameras offering excellent performance day or night.

The camera is available as indoor and outdoor versions for different applications.

System overview

The automatic zoom/focus lens wizard makes it easy for an installer to accurately zoom and focus the camera for both day and night operation. The wizard is activated from the PC or from the on-board camera push button making it easy to choose the workflow that suits best.

The AVF (Automatic Varifocal) feature means that the zoom can be changed without opening the camera. The automatic motorized zoom/focus adjustment with 1:1 pixel mapping ensures the camera is always accurately focused.

NDI-4512-A

Easy to install stylish indoor dome

Ideal for indoor use, the stylish design is suitable for installations where appearance and flexible coverage are important. The varifocal lens allows you to choose the coverage area to best suit your application. Using the proprietary pan/tilt/rotation mechanism, installers can select the exact field of view. Mounting options are numerous, including surface, wall, and suspended-ceiling mounting.











- ► Easy to install with auto zoom/focus lens, wizard and pre-configured modes
- ► Built-in Essential Video Analytics to trigger relevant alerts and quickly retrieve data
- ► Fully configurable H.265 multi-streaming
- ► High Dynamic Range to see every detail in both bright and dark areas of the scene
- ► Starlight camera technology with excellent lowlight performance

NDE-4512-A

Vandal resistant outdoor dome with varifocal lens Ideal for outdoor use, the IK10-rated design is suitable for installations where a vandal resistance is important. The camera is protected against water and dust to IP66 standards. The varifocal lens allows you to choose the coverage area to best suit your application. Mounting options are numerous, including surface, wall, and suspended-ceiling mounting.

Functions

Essential Video Analytics

The built-in video analysis reinforces the Intelligenceat-the-Edge concept and now delivers even more powerful features. Essential Video Analytics is ideal for use in controlled environments with limited detection ranges.

The system reliably detects, tracks, and analyzes objects, and alerts you when predefined alarms are triggered. A smart set of alarm rules makes complex tasks easy and reduces false alarms to a minimum. Metadata is attached to your video to add sense and structure. This enables you to quickly retrieve the relevant images from hours of stored video. Metadata can also be used to deliver irrefutable forensic evidence or to optimize business processes based on people counting or crowd density information. Calibration is quick and easy – just enter the height of the camera. The internal gyro/accelerometer sensor provides the rest of the information to precisely calibrate the video analytics.

Video - FLEXIDOME IP 4000i

Fast performance

The 60 frames per second mode provides for optimum performance in fast action scenes that ensures no critical data is lost.

Starlight performance

The latest sensor technology combined with the sophisticated image processing and noise suppression results in an exceptional sensitivity in color. The low-light performance is so good that the camera continues to provide excellent color performance even with a minimum of ambient light.

High Dynamic Range

The camera has High Dynamic Range. This is based on a multiple-exposure process that captures more details in the highlights and in the shadows even in the same scene. The result is that you can easily distinguish objects and features, for example, faces with bright backlight.

The actual dynamic range of the camera is measured using Opto-Electronic Conversion Function (OECF) analysis according to IEC 62676 Part 5. This method is used to provide standardized measurements, which can be used to compare different cameras.

Intelligent streaming reduces bandwidth and storage requirements

The low-noise image and the efficient H.265 compression technology provide clear images while reducing bandwidth and storage by up to 80% compared to standard H.264 cameras. With this new generation of cameras an extra level of intelligence is added with Intelligent Streaming. The camera provides the most usable image possible by cleverly optimizing the detail-to-bandwidth ratio. The smart encoder continuously scans the complete scene as well as regions of the scene and dynamically adjust compression based on relevant information like movement. Together with Intelligent Dynamic Noise Reduction, which actively analyzes the contents of a scene and reduces noise artifacts accordingly, bitrates are reduced by up to 80%. Because noise is reduced at the source during image capture, the lower bitrate does not compromise image quality. This results in substantially lower storage costs and network strain and still retain a high image quality and smooth motion.

Bitrate optimized profile

The average typical optimized bitrate in kbits/s for various frame rates when in H.265 mode is shown in the table:

| fps | 1080p | 720p |
|-----|-------|------|
| 60 | 712 | 525 |
| 30 | 600 | 450 |
| 12 | 438 | 329 |

| fps | 1080p | 720p |
|-----|-------|------|
| 5 | 284 | 213 |
| 2 | 122 | 92 |

Multiple streams

The multi-streaming feature delivers various H.264 or H.265 streams together with an M-JPEG stream. These streams facilitate bandwidth-efficient viewing and recording as well as integration with third-party video management systems.

The camera can run multiple independent streams that allows to set a different resolution and frame rate on the first and second stream. The user can also choose to use a copy of the first stream. The third stream uses the I-frames of the first stream for recording; the fourth stream shows a JPEG image at a maximum of 10 Mbit/s.

Two-way audio and audio alarm

Two-way audio allows the operator to communicate with visitors or intruders via an external audio line input and output. Audio detection can be used to generate an alarm if needed.

If required by local laws, the microphone can be permanently blocked via a secure license key.

Tamper and motion detection

A wide range of configuration options is available for alarms signaling camera tampering. A built-in algorithm for detecting movement in the video can also be used for alarm signaling.

Storage management

Recording management can be controlled by the Bosch Video Recording Manager or the camera can use iSCSI targets directly without any recording software.

Edge recording

The MicroSD card slot supports up to 2 TB of storage capacity. A microSD card can be used for local alarm recording. Pre-alarm recording in RAM reduces recording bandwidth on the network, or — if microSD card recording is used — extends the effective life of the storage medium.

Cloud-based services

The camera supports time-based or alarm-based JPEG posting to four different accounts. These accounts can address FTP servers or cloud-based storage. Video clips or JPEG images can also be exported to these accounts.

Alarms can be set up to trigger an e-mail or SMS notification so you are always aware of abnormal events.

Easy installation

Power for the camera can be supplied via a Powerover-Ethernet compliant network cable connection. With this configuration, only a single cable connection is required to view, power, and control the camera. Using PoE makes installation easier and more cost-effective, as cameras do not require a local power source.

The camera can also be supplied with power from +12 VDC/24 VAC power supplies. To increase system reliability, the camera can be simultaneously connected to both PoE and +12 VDC/24 VAC supplies. Additionally, uninterruptible power supplies (UPS) can be used, which will allow continuous operation, even during a power failure. For trouble-free network cabling, the camera supports Auto-MDIX which allows the use of straight or cross-over cables.

Automatic image rotation

The integrated gyro/accelerometer sensor automatically corrects the image orientation in steps of 90° if the camera is mounted at right angles or upside down. The sensor image can also be rotated manually through steps of 90°.

To efficiently capture details in long hallways without loss of resolution, mount the camera at right angles. The image is displayed upright at full resolution on your monitor.

True day/night switching

The camera incorporates mechanical filter technology for vivid daytime color and exceptional night-time imaging while maintaining sharp focus under all lighting conditions.

Hybrid mode

An analog video output enables the camera to operate in hybrid mode. This mode provides simultaneous high resolution HD video streaming and an analog video output via an SMB connector. The hybrid functionality offers an easy migration path from legacy CCTV to a modern IP-based system.

DORI coverage

DORI (Detect, Observe, Recognize, Identify) is a standard system (EN-62676-4) for defining the ability of a person viewing the video to distinguish persons or objects within a covered area. The maximum distance at which a camera/lens combination can meet these criteria is shown below:

1080p camera with 3-9 mm lens

| DORI | DORI definition | Distance 3 mm / 9 mm | Horizontal width |
|-----------|-----------------|----------------------|------------------|
| Detect | 25 px/m | 32 m / 126 m | 77 m |
| | 8 px/ft | 104 ft / 412 ft | 252 ft |
| Observe | 63 px/m | 13 m / 50 m | 30 m |
| | 19 px/ft | 41 ft / 164 ft | 100 ft |
| Recognize | 125 px/m | 6 m / 25 m | 15 m |
| | 38 px/ft | 21 ft / 82 ft | 50 ft |

| DORI | DORI definition | Distance 3 mm / 9 mm | Horizontal width |
|----------|-----------------|-------------------------|---------------------|
| Identify | 250 px/m | 3 m / 13 m | 8 m |
| | 76 px/ft | 10 ft / 41 ft | 25 ft |

Data security

Special measures have been put in place to ensure the highest level of security for device access and data transport. The three-level password protection with security recommendations allows users to customize device access. Web browser access can be protected using HTTPS and firmware updates can also be protected with authenticated secure uploads. The on-board Trusted Platform Module (TPM) and Public Key Infrastructure (PKI) support, guarantee superior protection from malicious attacks. The 802.1x network authentication with EAP/TLS, supports TLS 1.2 with updated cipher suites including AES 256 encryption.

The advanced certificate handling offers:

- Self-signed unique certificates automatically created when required
- Client and server certificates for authentication
- · Client certificates for proof of authenticity
- Certificates with encrypted private keys

Complete viewing software

There are many ways to access the camera's features: using a web browser, with the BVMS, with the free-of-charge Bosch Video Client or Video Security Client, with the video security mobile app, or via third-party software.

System integration

The camera conforms to the ONVIF Profile G, ONVIF Profile M, ONVIF Profile S, and ONVIF Profile T specifications. This guarantees interoperability between network video products regardless of manufacturer.

Third-party integrators can easily access the internal feature set of the camera for integration into large projects. Visit the Bosch Integration Partner Program (IPP) website (ipp.boschsecurity.com) for more information.

Regulatory information

HD standards

Complies with the SMPTE 274M-2008 Standard in:

- Resolution: 1920x1080Scan: Progressive
- Color representation: complies with ITU-R BT.709
- Aspect ratio: 16:9
- Frame rate: 25 and 30 frames/s

Complies with the SMPTE 296M-2001 Standard in:

- Resolution: 1280x720
- · Scan: Progressive
- Color representation: complies with ITU-R BT.709
- Aspect ratio: 16:9

Video - FLEXIDOME IP 4000i 4 | 8


• Frame rate: 25 and 30 frames/s

| Туре | Standard | | |
|-----------------------|---|-------------------------------|--|
| | NDI-4512-A | NDE-4512-A | |
| | EN 60950-1 | | |
| | UL 60950-1 | | |
| | | UL 60950-22 | |
| | CAN/CSA-C22.2 NO. 60 | CAN/CSA-C22.2 NO. 60950-1-03 | |
| | | CAN/CSA-C22.2 NO. 60950-22 | |
| | EN 50130-4 | | |
| | EN 50130-5, Class II (indoor in general, fixed equipment) | EN 50130-5 | |
| | FCC Part15 Subpart B, 0 | Class B | |
| | EMC directive 2014/30 | /EU | |
| | EN 55032 class B | | |
| | EN 55024 | | |
| | AS/NZS CISPR 32 (equa | ll to CISPR 32) | |
| | ICES-003 Class B | | |
| | VCCI J55022 V2/V3 | | |
| | EN 50121-4:2016 | | |
| | | EN 60950-22 | |
| ONVIF compli- ance | EN 50132-5-2; IEC 626 | 76-2-3 | |
| Product certifica- | CE, FCC, UL, cUL | | |

| Region | Regulatory compliance/quality marks | |
|--------|-------------------------------------|---------------------------------|
| Europe | CE | EU_DoC_F.01U.403.295 |
| USA | UL CAP | Cybersecurity Assurance Program |


Installation/configuration notes

NDI-4512-A



Dimensions in mm (inch)

NDE-4512-A



Dimensions in mm (inch)

Technical specifications

| Power | |
|----------------------------|---|
| Input voltage | +12 VDC ±5%, 24 VAC ±10% or Power-over-Ethernet (48 VDC nominal) |
| Power consumption (DC) | 7.15 W max. |
| Power consumption (AC) | 6.15 W max. |
| Power consumption (PoE) | 7 W max. |

Video - FLEXIDOME IP 4000i 5 | 8

| Power | |
|--|---|
| PoE IEEE standard | IEEE 802.3af (802.3at Type 1) Power level: Class 3 |
| Platform | |
| Common product plat- form | CPP7.3 |
| Sensor | |
| Sensor type | 1/2.8-inch CMOS |
| Effective pixels | 1920 (H) x 1080 (V); 2MP (approx.) |
| Video performance - Se | ensitivity |
| Sensitivity - (3100K, ref | lectivity 89%, 1/25, F1.3, 30IRE) |
| Color | 0.0225 lux |
| Mono | 0.0051 lux |
| Video performance - Dy | ynamic range |
| High Dynamic Range | 146 dB WDR |
| Measured according to IEC 62676 Part 5 | 107 dB WDR |
| Video streaming | |
| Video compression | H.265; H.264; M-JPEG |
| Streaming | Multiple configurable streams in H.264 or H.265 and M-JPEG, configurable frame rate and bandwidth. Regions of Interest (ROI) |
| Camera processing latency | <120 ms (max. average at 1080p60) |
| GOP structure | IP, IBP, IBBP |
| Encoding interval | 1 to 50 [60] fps |
| Encoding regions | Up to 8 areas with encoder quality settings per area |
| Video resolution (H x V |) |
| 1080p HD | 1920 × 1080 |
| Upright mode 1080p | 1080 × 1920 |
| 1.3 MP (16:9) | 1536 × 864 |
| Upright mode 1.3 MP (16:9) | 864 × 1536 |

| Video resolution (H x V) | |
|----------------------------------|--|
| 720p | 1280 × 720 |
| Upright mode 720p | 720 × 1280 |
| 480p SD | 640 × 480 |
| SD | 768 × 432 |
| D1 | 720 × 480 |
| Video functions | |
| Day/Night | Color, Monochrome, Auto (adjustable switch points) |
| Adjustable picture set- tings | Contrast, Saturation, Brightness |
| White Balance | 2000 to 10000K, 4 automatic modes (Basic, Standard, Sodium vapor, Dominant color), Manual mode and Hold mode |
| Shutter | Automatic Electronic Shutter (AES); Fixed (1/25[30] to 1/15000) selectable; Default shutter |
| Backlight compensation | On/off/Intelligent Auto Exposure (IAE) |
| Contrast enhancement | On/off |
| Signal-to-noise ratio (SNR) | >55 dB |
| Noise reduction | Intelligent Dynamic Noise Reduction with separate temporal and spatial adjustments |
| Sharpness | Sharpness enhancement level selectable |
| Intelligent defog | Intelligent Defog automatically adjusts parameters for best picture in foggy or misty scenes (switchable) |
| Privacy Masking | Eight independent areas, fully programmable |
| Video Analysis | Essential Video Analytics |
| Scene modes | Standard, Sodium lighting, Fast movement, Sensitivity boost, Dynamic backlight, Vibrant, Color only, Sports & gaming, Retail, License Plate Recognition (LPR) |
| Other functions | Image mirror, Image flip, Pixel counter, Video watermarking, Display stamping, Location |
| Camera rotation | Automatic detection with manual override |

Video - FLEXIDOME IP 4000i 6 | 8

| (0°/90°/ | 180°/ 270° |
|----------|------------|
|----------|------------|

| Analysis type Essential Video Analytics Features Rule based alarms and tracking Line crossing Enter /leave field Follow route Loitering Idle / removed object People counting Crowd density estimation 3D tracking Audio detection (if microphone used) Calibration / Geolocation Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) Alarm input 1 input | Video content analysis | |
|--|--------------------------|--|
| Line crossing Enter /leave field Follow route Loitering Idle / removed object People counting Crowd density estimation 3D tracking Audio detection (if microphone used) Calibration / Geolocation Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms max, 10 kohm typical Audio line out Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Analysis type | Essential Video Analytics |
| Enter /leave field Follow route Loitering Idle / removed object People counting Crowd density estimation 3D tracking Audio detection (if microphone used) Calibration / Geolocation Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out D.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Features | Rule based alarms and tracking |
| Follow route Loitering Idle / removed object People counting Crowd density estimation 3D tracking Audio detection (if microphone used) Calibration / Geolocation Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | Line crossing |
| Loitering Idle / removed object People counting Crowd density estimation 3D tracking Audio detection (if microphone used) Calibration / Geolocation Automatic based on gyro / accelerometer data and camera height Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out D.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | Enter /leave field |
| Idle / removed object People counting Crowd density estimation 3D tracking Audio detection (if microphone used) Calibration / Geolocation Automatic based on gyro / accelerometer data and camera height Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | Follow route |
| People counting Crowd density estimation 3D tracking Audio detection (if microphone used) Calibration / Geolocation Automatic based on gyro / accelerometer data and camera height Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | Loitering |
| Crowd density estimation 3D tracking Audio detection (if microphone used) Calibration / Geolocation Automatic based on gyro / accelerometer data and camera height Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | Idle / removed object |
| Audio detection (if microphone used) Calibration / Geolocation Automatic based on gyro / accelerometer data and camera height Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms at 16 Ohm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | People counting |
| Audio detection (if microphone used) Calibration / Geolocation Automatic based on gyro / accelerometer data and camera height Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | Crowd density estimation |
| Calibration / Geolocation Automatic based on gyro / accelerometer data and camera height Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | 3D tracking |
| tion and camera height Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | Audio detection (if microphone used) |
| Tamper detection Maskable Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Calibration / Geoloca- | Automatic based on gyro / accelerometer data |
| Audio detection Detection of audio to generate an alarm Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out Detection of audio to generate an alarm Others is a large of the corrected and alarm Motorized zonifocal (AVF) lens, IR corrected and IR corrected an | tion | and camera height |
| Optical Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Tamper detection | Maskable |
| Lens type 3 to 9 mm Automatic Varifocal (AVF) lens, IR corrected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Audio detection | Detection of audio to generate an alarm |
| rected DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Optical | |
| DC Iris F1.3 - 360 Lens mount Board mounted Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Lens type | |
| Lens mount Adjustment Motorized zoom/focus Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | |
| Adjustment Motorized zoom/focus Iris control Automatic iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | | DC Iris F1.3 - 360 |
| Iris control Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Lens mount | Board mounted |
| Day/Night Switched mechanical IR filter Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Adjustment | Motorized zoom/focus |
| Horizontal field of view 106° - 37° Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Iris control | Automatic iris control |
| Vertical field of view 55° - 21° Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Day/Night | Switched mechanical IR filter |
| Input/output Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Horizontal field of view | 106° - 37° |
| Analog video out SMB connector, CVBS (PAL/NTSC), 1 Vpp, 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Vertical field of view | 55° - 21° |
| 75 Ohm, approx. 500 TVL Audio line in 0.707 Vrms max, 10 kOhm typical Audio line out 0.707 Vrms at 16 Ohm typical Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Input/output | |
| Audio line out O.707 Vrms at 16 Ohm typical Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Analog video out | |
| Audio input Built-in microphone (can be permanently disabled) (only for NDI-4512-A) | Audio line in | 0.707 Vrms max, 10 kOhm typical |
| abled) (only for NDI-4512-A) | Audio line out | 0.707 Vrms at 16 Ohm typical |
| Alarm input 1 input | Audio input | |
| | Alarm input | 1 input |

| Input/output | |
|---------------------------------------|---|
| Alarm input activation | Short or DC 5V activation |
| Alarm output | 1 output |
| Alarm output voltage | 30 VDC, max. load 0.5 A |
| Ethernet | RJ45 |
| Audio streaming | |
| Standard | G.711, 8 kHz sampling rate L16, 16 kHz sampling rate AAC-LC, 48 kbps at 16 kHz sampling rate AAC-LC, 80 kbps at 16 kHz sampling rate |
| Signal-to-Noise Ratio | >50 dB |
| Audio Streaming | Full-duplex / half duplex |
| Local storage | |
| Internal RAM | 5 s pre-alarm recording |
| Memory card slot | Supports up to 32 GB microSDHC / 2 TB microS-DXC card. (A memory card of Class 6 or higher is recommended for HD recording) |
| Recording | Continuous recording, ring recording. alarm/ events/schedule recording |
| Network | |
| Protocols | IPv4, IPv6, UDP, TCP, HTTP, HTTPS, RTP/RTCP, RTSPS, IGMP, IGMP V2/V3, ICMP, ICMPv6, RTSP, FTP, Telnet, ARP, DHCP, SRTP, SNTP, SNMP (V1, MIB-II), 802.1x, DNS, DNSv6, DDNS (DynDNS.org, selfHOST.de, no-ip.com), SMTP, iSCSI, UPnP (SSDP), DiffServ (QoS), LLDP, SOAP, CHAP, digest authentication |
| Encryption | TLS1.0/1.2, AES128, AES256 |
| Ethernet | 10/100 Base-T, auto-sensing, half/full duplex |
| Connectivity | Auto-MDIX |
| Interoperability | ONVIF Profile S, ONVIF Profile G, ONVIF Profile M, ONVIF Profile T |
| NDI-4512-A | |
| Mechanical | |
| 3-axis adjustment (pan/tilt/rotation) | 350°/130°/350° |

135 x 102 mm (5.32 x 4 in)

Dimensions (Ø x H)

| Mechanical | | |
|--|--|--|
| 450 g (0.99 lb) | | |
| RAL 9003, RAL 9017 | | |
| Polycarbonate, clear with anti-scratch coating | | |
| Environmental | | |
| -20 °C to +50 °C (-4 °F to +122 °F) | | |
| -30 °C to +70 °C (-22 °F to +158 °F) | | |
| 5% to 93% relative humidity (non condensing) | | |
| Portugal | | |
| | | |

NDE-4512-A

| Mechanical | |
|---------------------------------------|--|
| 3-axis adjustment (pan/tilt/rotation) | 350° / 130° / 350° |
| Dimensions (Ø x H) | 145 x 131 mm (5.71x 5.14 in) |
| Weight | 1102 g (2.43 lb) |
| Color | RAL 9003, RAL 9017 |
| Housing material | Aluminum |
| Dome bubble | Polycarbonate, clear with anti-scratch coating |

| Environmental | | |
|-----------------------|--|--|
| Operating temperature | -40 °C to +50 °C (-40 °F to +122 °F) for continuous operation; | |
| | -34 °C to +74 °C (-30 °F to +165 °F) according to NEMA TS 2-2003 (R2008), para 2.1.5.1 using fig. 2.1 test profile | |
| Storage temperature | -40 °C to +70 °C (-40 °F to +158 °F) | |
| Operating humidity | 5% to 93% RH non condensing | |
| | 5% to 100% RH condensing | |
| Ingress protection | IP66 and NEMA 4X | |
| Impact protection | IK10 | |
| Country of origin | Portugal | |

Ordering information

NDI-4512-A Fixed dome 2MP HDR 3-9mm

Professional IP dome camera for indoor HD 60 fps surveillance with H.265 and Essential Video Analytics. NDAA compliant

Order number NDI-4512-A

NDE-4512-A Fixed dome 2MP HDR 3-9mm IP66

Vandal resistant IP dome camera for outdoor HD 60 fps surveillance with H.265 and Essential Video Analytics. NDAA compliant

Order number NDE-4512-A

Accessories

BUB-CLR-FDI Bubble, clear, indoor

Clear polycarbonate bubble for dome camera

Order number BUB-CLR-FDI

BUB-TIN-FDI Bubble, tinted, indoor

Tinted polycarbonate bubble for dome camera. Indoor

Order number BUB-TIN-FDI

BUB-CLR-FDO Bubble, clear, outdoor

Clear polycarbonate bubble for dome camera Outdoor

Order number BUB-CLR-FDO

BUB-TIN-FDO Bubble, tinted, outdoor

Tinted polycarbonate bubble for dome camera. Outdoor

Order number BUB-TIN-FDO

NBN-MCSMB-03M Cable, SMB to BNC, camera-cable, 0.3m

0.3 m (1 ft) analog cable, SMB (female) to BNC (female) to connect camera to coaxial cable Order number NBN-MCSMB-03M

NBN-MCSMB-30M Cable, SMB to BNC, cameramonitor/DVR

3 m (9 ft) analog cable, SMB (female) to BNC (male) to connect camera to monitor or DVR Order number **NBN-MCSMB-30M**

NDA-5031-PIP Pendant interface plate NDI-4/5000

Pendant interface plate for indoor FLEXIDOME IP 4000i / 5000i.

Order number NDA-5031-PIP

NDA-5030-PIP Pendant interface plate NDE-4/5000

Pendant interface plate for outdoor FLEXIDOME 4000i / 5000i.

Order number NDA-5030-PIP

NDA-ADT4S-MINDOME Surface mount box for dome

Surface mount box (Ø145 mm / Ø5.71 in) for dome cameras (for indoor camera variant, use together with NDA-ADTVEZ-DOME).

Order number NDA-ADT4S-MINDOME

NDA-ADTVEZ-DOME Adapter bracket for dome

Adapter bracket for indoor use (for indoor camera variant, use together with NDA-ADT4S-MINDOME). Order number **NDA-ADTVEZ-DOME**

NDA-FMT-DOME Inceiling flush mount for dome camera

In-ceiling flush mounting kit for dome cameras (Ø157 mm)

Order number NDA-FMT-DOME

NDA-SMB-MINISMB Surface mount box for dome camera 5.87"

Surface mount box (Ø149 mm / Ø5.87 in) Order number NDA-SMB-MINISMB

NDA-U-CMT Corner mount adapter

Universal corner mount, white Order number NDA-U-CMT

NDA-U-PMAL Pole mount adapter large

Universal pole mount adapter, white; large Order number NDA-U-PMAL

NDA-U-PMAS Pole mount adapter small

Pole mount adapter small

Universal pole mount adapter, white; small.

Order number NDA-U-PMAS

NDA-U-PMT Pendant pipe mount, 12" (31cm)

Universal pipe mount for dome cameras, 31 cm, white Order number NDA-U-PMT

NDA-U-PMTE Pendant pipe extension, 20" (50cm)

Extension for universal pipe mount, 50 cm, white Order number NDA-U-PMTE

NDA-U-PSMB Pendant wall/ceiling mount SMB

Surface mount box (SMB) for wall mount or pipe mount.

Order number NDA-U-PSMB

NDA-U-RMT Pendant parapet mount

Universal roof mount for dome cameras, white, for outdoor usage

Order number NDA-U-RMT

NDA-U-WMT Pendant wall mount

Universal wall mount for dome cameras, white Order number NDA-U-WMT

NDN-IOC-30M Cable, IP66 certified, waterproof

An IP66 certified cable for easy waterproof installation, for outdoor usage

Order number NDN-IOC-30M

NPD-5001-POE Midspan, 15W, single port, AC in

Power-over-Ethernet midspan injector for use with PoE enabled cameras; 15.4 W, 1-port

Weight: 200 g (0.44 lb) Order number NPD-5001-POE

NPD-5004-POE Midspan, 4 port x 15W, AC in

Power-over-Ethernet midspan injector for use with PoE enabled cameras; 15.4 W, 4-ports

Weight: 620 g (1.4 lb)

Order number NPD-5004-POE

UPA-1220-60 Power supply, 120VAC 60Hz,12VDC 1A

Power supply for camera. 100-240 VAC, 50/60 Hz In; 12 VDC, 1 A Out; regulated.

Input connector: 2-prong, North American standard (non-polarized).

Order number UPA-1220-60

VDA-PMT-AODOME Pipe mount for AUTODOME,

Sturdy outdoor pipe mount bracket for dome cameras (Ø166 mm)

Order number VDA-PMT-AODOME

VEZ-A2-WW Wall mount for PTZ dome, white

Wall mount (Ø145/149 mm) for dome cameras (use together with appropriate dome adapter bracket); white

Order number VEZ-A2-WW

NDA-LWMT-DOME Wall mount, L-shaped, for dome camera

Sturdy wall L-shaped bracket for dome cameras Order number NDA-LWMT-DOME

Represented by:

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5600 JB Eindhoven, The Netherlands

Bosch Sicherheitssysteme GmbH Robert-Bosch-Platz D-70839 Gerlingen

Bosch Security Systems, LLC 130 Perinton Parkway Fairport, New York, 14450, USA Asia-Pacific: Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943