INT-TX08-US Transmitter for 8 languages

www.boschsecurity.com





- ► Excellent audio quality
- ► Advanced digital technology
- ▶ Infra-red for freedom of movement for delegates
- ► Simultaneous interpretation
- ► User-friendly channel selection

The transmitter is the central element in the Integrus system. It accepts analogue or digital input, modulates these signals onto carrier waves and transmits these carrier waves to radiators located in the room.

Parts included

Quantity	Component
1	INT-TX08-US Transmitter for 8 languages

Technical specifications

Electrical

Maximum input level	18 dBV
Nominal impedance	32 Ω
Nominal input level	6 dBV
Input voltage	100 - 240 VAC

Power consumption	55 W
Power frequency	50 Hz; 60 Hz

Mechanical

Color	Gray
Dimensions (H x W x D)	92 mm x 440 mm x 410 mm
Mounting type	Rack-mounted
Weight	6.80 kg

Ordering information

INT-TX08-US Transmitter for 8 languages Integrus 8-channel transmitter. US version. Order number INT-TX08-US