

LBB4540/32 Pocket receiver for 32 languages

www.boschsecurity.com



BOSCH
Invented for life



These ergonomically designed pocket receivers incorporate the latest electronics technology - including a specially designed IC - to ensure maximum performance and a long battery lifetime. The pocket receivers can be used for both language and music distribution.

Functions

- Audio signal automatically muted when signal is too low, ensuring that the user receives only high quality audio
- Can be used with disposable batteries (2x AA alkaline batteries, not included) or environmentally-friendly NiMH rechargeable battery pack LBB 4550/10, (not included)
- No power used when headphone is disconnected
- Clip for easy wearing
- Measurement mode for easy checking of radiator coverage
- Attractive and stylish design
- Up to 200 hours operation with alkaline batteries
- Up to 75 hours operation with battery pack
- Recharges from empty to full capacity within 1 hour and 45 minutes

- ▶ Specially-designed IC for maximum performance and a long battery life time
- ▶ Recharging electronics integrated in the chip, ensuring optimum charging performance
- ▶ 2-digit LCD display with battery and reception status indication
- ▶ Number of available channels is always the same as the number of channels in use by the system, eliminating the need to scroll through unused channels

Controls and Indicators

- 2-digit LCD display with channel number, battery and reception status indication
- On/off button
- Volume control slide adjuster
- Channel selection up/down buttons
- Charging indicator LED

Interconnections

- 3.5 mm (0.14 in) stereo jack output socket for headphones
- Battery contacts for use with AA alkaline batteries
- Connector for use with LBB 4550/10 battery packs
- Charging contacts on the left-hand side of the pocket receiver for compatibility with LBB 4560 charging units

Certifications and approvals

Region	Regulatory compliance/quality marks	
Europe	CE	DECL EC LBB4540/32

Parts included

Quantity	Component
1	LBB4540/32 Pocket receiver for 32 languages

Technical specifications**Electrical**

IR irradiance level	4 mW/m ² per carrier
Angle of half sensitivity	± 50°
Headphone output level at 2.4 V	450 mVrms (speech at maximum volume, 32 ohm headphone)
Headphone output frequency range	20 Hz to 20 kHz
Headphone output impedance	32 ohm to 2 kohm
Max. signal-to-noise ratio	80 dB(A)
Supply voltage	1.8 to 3.6 V, nominal 2.4 V

Power consumption at 2.4 V (battery voltage)	15 mA (speech at maximum volume, 32 ohm headphone)
Power consumption (standby)	< 1 mA

Mechanical

Dimensions (H x W x D)	155 x 45 x 30 mm (6.1 x 1.8 x 1.2 in)
Weight	
excluding battery	75 g (0.16 lb)
including battery	125 g (0.27 lb)
Color	Charcoal with silver

Ordering information**LBB4540/32 Pocket receiver for 32 languages**

Integrus 32-channel pocket receiver.

Order number **LBB4540/32****Services****EWE-INTPRC-IW 12mths wrty ext Integrus Pocket Receiver**

12 months warranty extension

Order number **EWE-INTPRC-IW****Represented by:**

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: + 31 40 2577 284
emea.securitysystems@bosch.com
emea.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Ring 5
85630 Grasbrunn
Germany
www.boschsecurity.com

North America:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia