

PRA-WCP-EU Wall control panel, EU-style PRAESENSA





The wall control panel PRA-WCP-EU provides convenient local control of background music (BGM) in a zone covered by a PRAESENSA sound system. In the PRAESENSA system it is possible to configure a set of selectable music sources, the volume control range, and the operating zone for each wall control panel. Control is quick and intuitive, with a single knob for the rotate and push select actions. The color LCD provides clear user feedback. It is possible to manage user access with a PIN to restrict operation to authorized staff.

The PRA-WCP-EU comes with a white front, knob and square wall plate. A black front, knob and wall plate are included for easy exchange on-site. It fits in the standard European round recess electrical back box for flush-mount installation.

Functions

IP-network connection

- Direct connection to the IP-network. One shielded Ethernet cable is sufficient for Power over Ethernet and data exchange.
- The wall control panel communicates the BGM settings directly to the system controller. The system controller adjusts the source and level of the involved amplifier channels accordingly.
- Because only control information is exchanged, no audio data, the occupied network bandwidth for this function is minimized.

Operation


 The volume settings of the BGM have configurable minimum and maximum levels.

- ► Easy to read color TFT display
- ► Local control of music source and volume in different zones
- ▶ PoE powered device
- ► Fits in the standard European round recess back box
- ► Interchangeable white and black front
- Selection of the BGM source from a list of BGM channels that are assigned to the zone under control
- Selection through a single rotary knob with push action.
- · Clear user feedback through the backlit color LCD.
- Optional access control through PIN entry to restrict operation to authorized staff.

Installation


- The wall control panel fits in a standard European round recess electrical back box for flush-mount installation with 60 mm of inside diameter and 60 mm of depth. Square wall plates (white and black) are included.
- IP-network connection through a single cable with BJ45 connector.
- The device comes with a black and a white front cover and wall plate, exchangeable to match the environment.

Connection and functional diagram





Front side indicator




Front side control


	Function select and control	Rotary/push encoder
5	Device reset to factory default	Button (behind the cover)


Rear side indicators


뫎	100 Mbps network 1-2 1 Gbps network 1-2	Yellow Green
Rea	side interconnection	
器	Network port (PoE PD)	

Dimensions









mm

11.5

Architects' and engineers' specifications

The IP networked wall control panel shall be designed exclusively for use with Bosch PRAESENSA systems. It shall provide an interface for control data over OMNEO using Ethernet. It shall receive Power over Ethernet (PoE) through its network connection. It shall fit in a standard electrical back box for flushmount installations. The wall control panel shall be an interface to the sound system to select a background music channel in a zone and change its volume level. It shall have a single push/rotate knob

and a full color LCD with backlight for easy navigation and clear indication of the operating zone, selected channel and actual volume level. It shall be fit for operation by untrained people, but it shall also have configurable PIN-code access to restrict access to authorized staff. The wall control panel shall be marked for CE and be compliant with the RoHS directive. Warranty shall be three years minimum. The wall control panel shall be a Bosch PRA-WCP-EU or PRA-WCP-US.

Regulatory information				
Regulatory areas				
Immunity	EN 55035			
Emissions	EN 55032 EN 61000-6-3 ICES-003 ANSI C63.4 FCC-47 part 15B class A			
Environment	EN/IEC 63000			

Parts included		
Quantity	Component	
1	PRA-WCP-EU Wall control panel, EU-style, white version	
1	Wall plate for PRA-WCP-EU, white	
1	Wall plate for PRA-WCP-EU, black	
1	Black front panel and knob	
1	Quick installation guide	
1	Safety and security information	

Technical specifications

Electrical

Display		
Display size (in)	1.77 in	
Display color	Color	
Display type	TFT	
Display resolution (pixels) (W x H)	128 x 160 px	
Brightness	480 cd/m2	

Power transfer		
Power over Ethernet (PD)	PoE IEEE 802.3af Class 1	
Nominal voltage (VDC)	48 VDC	
Input voltage (VDC) (tolerance)	37 VDC - 57 VDC	
Power consumption (W) (maximum)	1.30 W	

Network interface	
Ethernet type	100BASE-TX; 1000BASE-T

Protocols / standards	TCP/IP; AES70
Number of Ethernet ports	1
Reliability	
Mean time between failures (MTBF) (h) (calculated according to Telcordia SR 332 Issue 3)	2,433,404 h
Environmental	
Operating temperature (°C)	-5 °C − 50 °C
Operating temperature (°F)	-13 °F − 131 °F
Storage temperature (°C)	-30°C − 70°C
Storage temperature (°F)	-22 °F − 158 °F
Operating relative humidity, non- condensing (%)	5% - 95%
Air pressure (hPa)	560 hPa – 1,070 hPa
Installation altitude (m)	-500 m – 5,000 m
Installation altitude (ft)	-1,640 ft – 16,404 ft
Operating vibration	
Amplitude (mm)	< 0.7 mm
Acceleration (G)	< 2 G
Bump (transport) (G)	< 10 G (IEC 60068-2-27)
Mechanical	
Dimensions (H x W x D) (mm)	81 mm x 70 mm x 47.3 mm
Dimensions (H x W x D) (in)	3.19 in x 2.76 in x 1.86 in
Dimensions of wall box (Ø x D) (mm)	60 mm x 60 mm
Dimensions of wall box (Ø x D) (in)	2.36 in x 2.36 in
IP rating	IP20
Material	Plastic (PC/ABS – UL94-5VA)
Color (RAL) (front cover with knob)	RAL 9017 Traffic black; RAL 9003 Signal white
Weight (kg)	0.10 kg

0.22 lb

Weight (lb)

Ordering information

PRA-WCP-EU Wall control panel, EU-style

Network connected, PoE powered wall control panel for local control of background music.

Order number PRA-WCP-EU | F.01U.394.535

Represented by:

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5600 JB Eindhoven, The Netherlands www.boschsecurity.com/xc/en/contact/ www.boschsecurity.com

Germany:
Bosch Sicherheitssysteme GmbH
Robert-Bosch-Platz 1
D-70839 Gerlingen
www.boschsecurity.com

North America: Bosch Security Systems, LLC 130 Perinton Parkway Fairport, New York, 14450, USA www.boschsecurity.com Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
www.boschsecurity.com/xc/en/contact/
www.boschsecurity.com/