

# **PVA-15ECS Emergency call station**PAVIRO



- ► Call station with soft touch button
- ▶ Built-in alarm buttons and key switch for emergency use
- ▶ 15 freely programmable buttons
- ► Customization via built-in display and keys
- ► EN 54-16 system certification


The PVA-15ECS is the emergency call station for the PAVIRO system.

The emergency call station has a gooseneck microphone with pop shield and permanent monitoring, a total of 20 buttons, an illuminated display panel, and an integrated loudspeaker, like the standard call station PVA-15CST. In addition, two alarm buttons with protective covers and a key switch are factory fitted as standard.

The call station can be modified to suit the user's requirements by connecting up to five PVA-20CSE call station extensions, each with 20 customizable selection buttons.


#### Other properties:

- Five menu/function keys (pre-programmed) one green or one yellow indicator light per button
- 15 selection buttons (customizable) two indicator lights (green/red) per button
- Numeric zone selection (can be activated during IRIS-Net configuration)
- Label with transparent covering the label can be changed at any time
- Can be used as a standing or desk/rack flushmounted device
- Internal monitoring with error logging complies with all relevant national and international standards
- Easy configuration use of the Configuration Wizard or IRIS-Net software



- 1 Selection buttons
- 2 Alarm buttons
- 3 Area for factory fitted key switch and alarm buttons
- 4 Voice alarm indicator light
- 5 Combined fault warning indicator light
- 6 Power indicator light
- 7 Microphone

- 8 Loudspeaker
- 9 Display
- 10 ESC button
- 11 ↑ button
- 12 DEL button
- 13 ↓ button
- 14 ⊌ button



- 1 EXT OUT port
- 2 CST BUS port
- 3 LINE port
- 4 MIC port

| Cer | τιτι | cat | lor | is a | ne | ap | pro | vais |
|-----|------|-----|-----|------|----|----|-----|------|
|     |      |     |     |      |    |    |     |      |

# **Emergency standard certifications**

Europe EN 54-16

**Emergency standard compliance** 

UK BS 5839-8

| <b>Emergency</b> | standard v   | comi   | oliance  |
|------------------|--------------|--------|----------|
| LINCISCIO        | y Stailaal a | COIIII | JIIGIICC |

Austria ÖNORM F 3033

| Environmental directive compliance |   |  |  |
|------------------------------------|---|--|--|
| Safety                             | EN 62368-1  |  |  |
| Immunity                           | EN 50130-4  |  |  |
| Emissions                          | EN 61000-6-3<br>ICES-003<br>FCC-47 part 15B class A |  |  |
| Environment                        | EN 50581  |  |  |
| Maritime                           | EN 60945  |  |  |

| Conformity         |        |
|--------------------|--------|
| Europe             | CE/CPR |
| USA                | FCC    |
| Canada             | ICES   |
| Australia          | RCM    |
| Russian Federation | EAC    |
| Environment        | RoHS   |

# Parts included

| Quantity | Component                     |
|----------|-------------------------------|
| 1        | PVA-15ECS                     |
| 1        | Patch cable (3 meters)        |
| 7        | Blank paper strips            |
| 1        | Strain relief (bracket)       |
| 2        | Screws for strain relief      |
| 1        | Cover release tool            |
| 1        | Operation manual              |
| 1        | Important safety instructions |

# **Technical specifications**

## **Electrical**

| CAN BUS port 10, 20, or 62.5 kbit/s, 1 x RJ-45, |
|---|
| max. length 1000 m                              |

| Maximum mic input level   | -21 dBu   |
|---|---|
| Maximum line input level  | +4 dBu  |
| Maximum NF output level   | +12 dBu   |
| Microphone<br>Nominal acoustic input level<br>Frequency response<br>Signal to noise ratio | 85 dBSPL<br>250 Hz - 10 kHz (-10dB)<br>> 60dB   |
| Buttons   | 5 pre-programmed, 15 programmable zone/function keys  |
| Built-in alarm buttons  | 2 alarm buttons (with transparent<br>cover) for broadcasting an alarm<br>signal. The button feed lines are<br>monitored by the call station.                                      |
| Built-in key switch   | Key switch for preventing unauthorized use of the call station. The key switch feed lines are monitored by the call station.  |
| Indicator lights  | Power (green), Fault (yellow), Alarm<br>(red) Green or yellow LED per pre-<br>programmed menu button Green and red LED per<br>programmable zone/function key                      |
| LC display  | Back-lit LC display (122 x 32 pixel)  |
| Ports   | 1 CST BUS port (Control data + Audio + Power supply, RJ-45) 1 audio source (line level, phone jack) 1 microphone port (phone jack) 1 EXT OUT port (call station extension, RJ-12) |
| DC power input  | 15-58 V   |
| Maximum supply current (without call station extensions)                                  | Standby/Idle/Announcement/Alert: 24 V / 80 mA / 1.92 W  |
| Maximum supply current (with 5 call station extensions)                                   | Standby/Idle/Announcement/Alert: 24 V / 190 mA / 4.56 W   |

#### Mechanical

| Color                                       | RAL 9017 (traffic black)                     |
|---|--|
| Product dimensions (Height x Width x Depth) | 166 mm x 200 mm x 66 mm (without microphone) |

| Net weight      | 0.7 kg |
|-----------------|--------|
| Shipping weight | 1.3 kg |

#### **Environmental**

| Operating temperature             | -5 °C to +45 °C (+23 °F to +113 °F)  |
|-----------------------------------|--------------------------------------|
| Storage and transport temperature | -25 °C to +70 °C (-13 °F to +158 °F) |
| Humidity (non-condensing)         | 5% to 90%                            |
| Altitude                          | Up to 2000 m                         |




Fig. 1: Circuit diagram




Fig. 2: Dimensions of Call Station

# **Ordering information**

# **PVA-15ECS Emergency call station**

Emergency call station for PAVIRO system with built-in alarm buttons and key switch.

Order number **PVA-15ECS | F.01U.322.533** 

# **Accessories**

## **PVA-20CSE Call station extension**

Call station extension for the PAVIRO system; has 20 customizable selection buttons.

Order number **PVA-20CSE | F.01U.298.723** 

## Services

EWE-CLSBAS-IW 12 mths wrty ext. Call Station basic 12 months warranty extension Order number EWE-CLSBAS-IW | F.01U.360.680

#### Represented by:

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5600 JB Eindhoven, The Netherlands Phone: + 31 40 2577 284 emea.securitysystems@bosch.com emea.boschsecurity.com Germany: Bosch Sicherheitssysteme GmbH Robert-Bosch-Ring 5 85630 Grasbrunn Germany www.boschsecurity.com North America:
Bosch Security Systems, LLC
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.us

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia